

# Power and Light Cord Reels | Series L4000 / L5000 / L7000

	Dimensions - Size Index							
	1		2		3		4	
	in	mm	in	mm	in	mm	in	mm
<b>A</b>	13 <sup>1</sup> / <sub>4</sub>	337	14 <sup>1</sup> / <sub>2</sub>	368	17 <sup>1</sup> / <sub>2</sub>	445	17 <sup>1</sup> / <sub>2</sub>	445
<b>B</b>	12 <sup>5</sup> / <sub>8</sub>	321	13 <sup>1</sup> / <sub>2</sub>	343	16 <sup>1</sup> / <sub>2</sub>	419	16 <sup>1</sup> / <sub>2</sub>	419
<b>C</b>	8	203	9 <sup>3</sup> / <sub>4</sub>	248	9 <sup>3</sup> / <sub>4</sub>	248	9 <sup>3</sup> / <sub>4</sub>	248
<b>D</b>	2 <sup>1</sup> / <sub>2</sub>	64	2 <sup>1</sup> / <sub>2</sub>	64	2 <sup>1</sup> / <sub>2</sub>	64	2 <sup>1</sup> / <sub>2</sub>	64
<b>E</b>	9 <sup>3</sup> / <sub>8</sub>	239	10 <sup>1</sup> / <sub>2</sub>	267	10 <sup>1</sup> / <sub>2</sub>	267	12 <sup>1</sup> / <sub>2</sub>	318
<b>F</b>	1 <sup>3</sup> / <sub>4</sub>	44	2 <sup>1</sup> / <sub>8</sub>	54	2 <sup>1</sup> / <sub>8</sub>	54	2 <sup>1</sup> / <sub>8</sub>	54



Model with Cord	Cord Ending	Cord Specifications					Volts	Amps	Shipping Weight		Size Index #	
		AWG	mm	# Cond	ft	m			Type	lbs		kg
L 4035 163 1	*Incandescent	16	1.33	3	35	11	SJTOW	125	13	23	10	1
L 4050 163 1	*Incandescent	16	1.33	3	50	15	SJTOW	125	13	27	12	1
L 4035 A 163 5**	*Incandescent	16	1.33	3	35	11	SJEOOW	125	13	25	11	1
L 4050 A 163 5**	*Incandescent	16	1.33	3	50	15	SJEOOW	125	13	28	13	1
L 5245 A 163 6X**	Fluorescent	16	1.33	3	45	14	SE00W	125	0.3	39	18	2
L 4035 162 2	Fluorescent	16	1.33	2	35	11	SJTOW	125	0.3	25	11	1
L 4050 162 2	Fluorescent	16	1.33	2	50	15	SJTOW	125	0.3	26	12	1
L 4035 163 8	Fluorescent Light and Outlet	16	1.33	3	35	11	SJTO	125	10	25	11	1
L 4050 163 8	Fluorescent Light and Outlet	16	1.33	3	50	15	SJTO	125	10	27	12	1
L 4035 163 10	LED	16	1.33	3	35	11	SJTOW	125	13	26	12	1
L 4050 163 10	LED	16	1.33	3	50	15	SJTOW	125	13	28	13	1

For indoor non-weather tight applications only. \*Incandescent bulb 75 watt max. Series L4000 and L5000 models UL listed at 125 Volt 60 HZ single phase. \*\*Models equipped with automatic on/off switch that activates power. **NOTE:** Swing brackets should be used if cords are pulled at more than 45°. Reference page 4 for guide arm positions.



## Cord Options

	<b>#1 - Incandescent Light</b> <ul style="list-style-type: none"> <li>Single receptacle tool tap</li> <li>Push-through switch, metal grounded guard</li> </ul>
	<b>#2 - Fluorescent Light</b> <ul style="list-style-type: none"> <li>Durable shock absorbing lamp holder</li> <li>Shatter-resistant tube with switch</li> </ul>
	<b>#5 - Incandescent Light</b> <ul style="list-style-type: none"> <li>Rubber handle with vinyl-coated cage w/o switch or receptacle</li> <li>Automatic on/off switch at reel guide arm</li> <li>Complies with NEC #511-3, f., portable lighting equipment; meets OSHA requirements</li> </ul>
	<b>#6 - Fluorescent Light</b> <ul style="list-style-type: none"> <li>Explosion proof 13 watt fluorescent hand lamp</li> <li>Automatic on/off switch at reel guide arm</li> <li>Suitable for Class 1, group C and D locations <b>Note:</b> Reel is not explosion-proof.</li> </ul>
	<b>#8 - Fluorescent Light</b> <ul style="list-style-type: none"> <li>120 V - 15 Amp receptacle in-line on lamp handle</li> <li>Scratch guard protects lamp cover</li> </ul>
	<b>#10 - LED Light</b> <ul style="list-style-type: none"> <li>Two ultra high intensity 4-watt LEDs; single 3-watt end spot light</li> <li>Polycarbonate shatter-resistant light tube</li> <li>In-line tool tap, NEMA 5-15R configuration maximum 12 Amp draw</li> </ul>

## Auto-Switch Light Cord Reels

Models equipped with an automatic on/off switch incorporate a guide arm-mounted switch that activates power with a pull of the cord.



L 5245 A 163 6X



Note: Reel is not explosion proof

### Fluorescent Hand Lamp - order model 1 163 3 8

- One foot #16/3 conductor SJTOW-A yellow cord with molded NEMA 5-15P plug
- SAF-T-TIE keeps the light plugged into receptacle